

## Beacon Adapters

### p/n BN2010 – 372 to FMX

(A) 12 Pin DTM Female (372)	(B) 12 pin DTM Male (FMX)	Color	Notes
5	5	Yellow	Ground
6	4	Red	Tx
8	3	Brown	Rx
10	9	Blue	12v Power
11	8	Black	Ground



### p/n BN2011 – FMX to 372

(A) 12 Pin DTM Female (FMX)	(B) 12 pin DTM Male (372)	Color	Notes
3	8	Brown	Tx
4	6	Red	Rx
5	5	Yellow	Sig ground
8	11	Blue	Ground
9	10	Black	12V power

Length 4" Use bare wires with heatshink.