

Beacon v3.0 to Paradyne

p/n BN2012

this cable is used when plugging the Beacon directly into paradyne.

Beacon 12 Pin# (A) DTM Female	Paradyne (12 pin) (B) DT 12Pin Black	Color	Notes
5	9 YELLOW/Black	Yellow	Ground
6	12	Red	Tx
8	1	Brown	Rx
10	8	Blue	12v Power
11	9 Yellow/Black	Black	Ground



For building cables use $\frac{1}{2}$ of the JD cable length.

Heat shrink long enough to include label on Beacon side